



Vlastné straty (spotreba) magnetických tlmiviek pre výbojky.

	výbojka	V/Hz	A	odp. Ohm	vlastná strata W pri 20st.C
Ortuť	50	230/50	0,62	311	10
	80	230/50	0,8	221	11,5
	125	230/50	1,15	145	14
	250	230/50	2,15	77	20
	400	230/50	3,25	51	25
	700	230/50	5,45	30	33
	1000	230/50	7,6	20	37
Sodík	50	230/50	0,76	262	11,5
	70	230/50	1	198	13,5
	100	230/50	1,2	158	16
	150	230/50	1,8	105	20
	250	230/50	3	64	26
	400	230/50	4,45	42,1	39
	600	230/50	6,2	29,9	39
	1000	230/50	10,3	18,1	60
MH	35	230/50	0,53	371	8
	70	230/50	0,98	198	13,5
	100	230/50	1,15	158	15
	150	230/50	1,8	105	20
	250	230/50	2,15	77	20
	250	230/50	3	64	26
	400	230/50	3,5	50	29
	400	230/50	4,3	42,1	39
	1000	230/50	8,25	20	44
	1000	230/50	9,5	18,1	52
	2000	230/50	16,5	10	88
	2000	380	8,8	28	60
	2000	380	10,3	25,5	75